


JUNCTION BOX REQUIREMENTS

For straight pulls
For opposite wall
For right angle turns

Min. 'B' = 8 diameters of larger conduit
Min. 'C' = 6 diameters of larger conduit
Min. 'D' = 8 diameters of larger conduit



CONDUIT LOCATION FOR LOCK NUT AND BUSHING CLEARANCE - 'A'										
Conduit Size	<u>1</u> "	<u>3</u> 11	1"	1 1 "	112"	2"	2 <u>1</u> "	3	3 <u>1</u> "	4"
Minimum Clearance	1"	1"	1 1 "	1 3 "	1 1 "	1 3 "	2 1 "	2 <u>1</u> "	2 7 "	3 <u>1</u> "

MINIMUM SPACING BETWEEN CONDUIT CENTERS - 'E'											
Size	<u>1</u>	<u>3</u>	1"	1 ¹ / ₄ "	1 1 "	2"	2 <u>1</u> "	3"	3 <u>1</u> "	4"	
<u>1</u>	1 1 "	1 3 "	1 5 "	7 <u>7</u> 8	2"	গুঁ	2 5 "	3"	3 <u>1</u> "	3 5 "	
<u>3</u> .,		1 1 "	13"	2"	2 1 "	2 <u>1</u> "	2 3 "	¹ အ က် ဘ	- - - - - - - - - - - - - - - - - - -	3 3 "	
1"			2"	2 1 "	2 3 "	2 3 "	3"	3 3 "	3 5 "	4"	
1 1 "				2 <u>1</u> "	2 5 "	3"	3 1 "	35 33 34	3 7 "	4 <u>1</u> "	
1 1 "					2 3 "	3 <u>1</u> "	3 3 "	3 3 "	4"	4 3 "	
2"						3½" 3½"	3 <u>3</u> "	4 <u>1</u> "	4 3 "	4 3 "	
2 <u>1</u> "							4"	4 3 "	4 <u>5</u> "	5"	
3"								4 <u>3</u> "	5"	5 <u>3</u> "	
3 <u>1</u> "									5 <u>1</u> "	5 <u>5</u> "	
Δ"										6"	

Alternate design may be submitted to the Engineer for approval.

Approved galvanized steel covers may be substituted for cast iron.

Fit grounding buttons with $3/8" \times 3/4"$ brass screws unless specified otherwise.

Type, size and location of holes will be shown on the plans.

Use slip holes only for junction box drains unless specified otherwise

1 In locations subject to pedestrian traffic, install junction box covers with approved anti-skid pattern.

Contract Items:

Handholes and Junction Boxes

